3015

FM FRONT END FL412U

INPUT FM 300Ω

TR102 2SC829C

TR103 2SC536G

TR104 2SA564

TR105

TR106

TR107

TR101 2SC829C

IC101 TA7061

IC102 TA7061

K101 CF-10M-12

K102 CF-10M-24

VR901 100KB

VR902 250KB

VR903 250KB

VR101 220KB

MUTING

FM IF CIRCUIT "FM-IC-8"

T101 F211E

L105 47μH

L102 47μH

TR105, TR106 2SC536G
TR107 2SC829C

TR901 2SC828

MPX

TUNING METER

FUNCTION SWITCH

A M FM FM ST.

TR201 2SC829

TR202 2SC829

TR203 2SC829

TR204 2SC829

T201 RL-35

T202 RL-36

T203 CFU-60A

T204 A10D

AM CIRCUIT "AM-RF-3A"

MPX DECODER "MX-H3"

TR301 CDC10045

TR302 2SA49

TR303 2SA49

TR304 2SC828

TR305 2SB173

TR306 2SB173

L301 RL-31

T301 RL-32

T302 RL-32

L302 RL-26

L303 RL-13

D303~D306 1S1889

R317~320 1.5K

F301 RL-37 SPEC FILTER

F302 RL-37 SPEC FILTER

ST. IND. 14V 80mA

TR401 2SC536G

TR402 2SC536G

NOISE FIL.

OUTPUT AMP. "MA-3"

VR9041 VR9042

RIGHT LEFT OUT PUT

RIGHT LEFT OUT PUT

D902 IS-1850

PL1-PL3 6.3V 25mA

BROWN BLUE RED ORANGE WHITE YELLOW

SWITCHED MAX. 100W

220~240V 0.5A
100~117V 1A

POWER

117V 100V 240V 220V

FUNCTION

(1) A M
(2) F M
(3) FM STEREO

CONTROLS

VR101 ST. MONO THRESHOLD CONTROL
VR301 SEPARATION CONTROL
VR901 MUTING LEVEL CONTROL
VR902 MUTING CONTROL
VR903 MUTING CONTROL
VR904 OUT PUT CONTROL

RESISTORS

K·· KILO OHM M·· MEG OHM
▲·· COMPOSITION RESISTORS 10% TOLERANCE ½ WATT
NON MARK·· CARBON RESISTORS 10% TOLERANCE ¼ WATT

CAPACITORS

10% TOLERANCE UNLESS OTHERWISE NOTED
(MY) ·· MYLAR FILM CAPACITORS
(P) ·· POLY STYROL CAPACITORS
⊣⊢ ·· ELECTROLYTIC CAPACITORS
NON MARK ·· CERAMIC CAPACITORS

SCOTT®

SUBJECT TO MINOR CHENGES OF PARTS WITHOUT PRIOR NOTICE